

PINTEK

Differential Probe

★ *High Sensitivity!*

★ *High Voltage!*

DP-35

35 MHz / 1600 Vp-p

- *High Sensitivity, High Voltage Model.*
(高靈敏度, 高電壓機種)
- *35 MHz / 1600 Vp-p Max.*
(最大量測 35 MHz / 1600 Vp-p)
- *Input Impedance 8 MΩ // 2.5 PF*
(輸入阻抗 8 MΩ // 2.5 PF)
- *X10, X100 Attenuator, Easy to Convert.*
(X10, X100 採用十進位換算不易出錯)
- *Separating Design (Standard No. 114205)*
Convenient & Durable.
(分離式設計專利第114205號, 方便耐用)

Max Input	X100	X10
DC V	± 800V	± 80V
AC Vrms	560V	56V
AC Vp-p	1600V	160V

PINTEK DP-35
DIFFERENTIAL PROBE
DC - 35MHz

OUTPUT INTO 1MΩ
EXT. POWER 5V/2A DC



Pintek Electronics Co., Ltd
www.pintek.com.tw